

## ON ANYONIC PROPAGATORS

WELLINGTON DA CRUZ

ABSTRACT. We consider a simple action for a fractional spin particle and a path integral representation for the propagator is obtained in a gauge such that the constraint embodied in the Lagrangian is not an obstacle. We obtain a propagator for the particle in a constant electromagnetic field via the path integral representation over velocities, which is characterized by arbitrary boundary conditions and the absence of time derivatives following integration over bosonic variables.

There are various actions in the literature[1] for particles with fractional spins, called anyons[2], that can be present in nature and explain phenomena such as the fractional quantum Hall effect and high temperature superconductivity[3]. Such models have been constructed in at least two ways: one is coupling to some matter field a statistical field of the Chern-Simons type that changes the statistics; and the other is the group-theoretical method that implies a classical mechanical model with a Poincaré invariant Lagrangian which is quantized[4, 5]. In this Letter, we consider a simple action obtained by the latter approach with minimal extension of the phase space that preserves all canonical structure of the space-time and spin algebra. We propose a path integral representation for the propagator in a convenient gauge. In[4], the following continuous family of Lagrangians for free anyons was obtained

$$L_s = \frac{1}{2e} \left( \dot{x}_\mu - \frac{s \dot{q} f'_\mu}{m f \cdot \dot{x}} \right)^2 + \frac{e m^2}{2} - \frac{\alpha m e \dot{q}}{f \cdot \dot{x}}, \quad (1)$$

where  $m$  and  $\alpha$  are respectively the mass and the helicity of the anyon, and  $s$  is an arbitrary constant deduced from the Casimir of the spin algebra,  $S^2 = -s^2$ . The functions  $f_\mu$  satisfy the non-linear differential equation

$$f_\mu = \epsilon_{\mu\alpha\beta} f'^\alpha f^\beta \quad (2)$$

and we obtain the relations

---

*Date:* December, 1999.

$$f^2 = 0, \quad f'^2 = -1, \quad f'' \cdot f = 1, \quad (3)$$

with  $f' = \frac{df}{dq}$ . On the other hand, we have that  $S_\mu = \pi f_\mu + s f'_\mu$ , so we get,  $S_\mu f'^\mu = -s$ ,  $S_\mu f^\mu = 0$ ,  $S'_\mu f^\mu = s$ ,  $S'_\mu f'^\mu = -\pi$ . The equation  $\dot{f} - \dot{q}f' = 0$  is equivalent to Eq. (2) and we have also

$$\dot{f}' - \frac{\partial \dot{q}}{\partial q} f' - \dot{q} \frac{\partial f'}{\partial q} = 0$$

and  $f_\mu = a_\mu q^2 + b_\mu q + c_\mu$ , with  $a_\mu = (1, 0, -1)$ ,  $b_\mu = (-1, 1, 1)$ ,  $c_\mu = \frac{1}{2}(1, -1, 0)$ . In this way, we extract for  $q$  not constant the condition  $\frac{\partial \dot{q}}{\partial q} = 0$ . The Lagrangian is subject to the constraint,  $\sigma(f \cdot \dot{x}) = e \dot{q}$ , and with  $\dot{x}_\mu = e p_\mu + \sigma S_\mu$ , we obtain  $\dot{q} = \sigma(f \cdot p)$  which satisfies and gives us that  $f' \cdot p = 0$ . Then,  $\dot{x} \cdot f' = -\sigma s$  and  $\pi(f \cdot p) = -\alpha m$ , that is,  $S_\mu p^\mu + \alpha m = 0$  and  $\dot{x} \cdot f = e f^\mu p_\mu$ , and in the gauge  $\dot{\sigma} = 0$ ,  $\dot{e} = 0$ , we have  $\dot{q} = m f \cdot \dot{x}$ , so  $\sigma = e m$  and  $p^2 - m^2 = 0$ .

Now, we consider the path integral representation for the anyonic propagator with the action,  $\mathcal{A} = \int_0^1 L_s d\tau$ . In that gauge, we verify that the continuous family of Lagrangians appears as

$$L_s = \frac{\dot{x}^2}{2e} + \frac{s^2}{2e} + \frac{e}{2}(m^2 - 2m^2\alpha). \quad (4)$$

In this way, we propose the path integral representation for the free fractional spin particle as

$$\begin{aligned} \mathcal{F}(x_{out}, x_{in}) &= \frac{i}{2} \int_0^\infty de_0 \int_{x_{in}}^{x_{out}} \mathcal{D}x \mathcal{D}e M(e) \delta(\dot{e}) \\ &\times \exp \left\{ -\frac{i}{2} \int_0^1 \left[ \frac{\dot{x}^2}{e} + e\mathcal{M}^2 + \frac{s^2}{e} \right] d\tau \right\}, \end{aligned} \quad (5)$$

where  $\mathcal{M}^2 = m^2 - 2m^2\alpha$  and the delta functional takes into account the gauge,  $\dot{e} = 0$ . We define the measure

$$M(e) = \int \mathcal{D}p \exp \left\{ \frac{i}{2} \int_0^1 e p^2 d\tau \right\}, \quad (6)$$

such that, making the substitution

$$\sqrt{e}p \rightarrow p, \quad \frac{x - x_{in} - \tau \Delta x}{\sqrt{e}} \rightarrow x, \quad \Delta x = x_{out} - x_{in},$$

we obtain the new boundary conditions  $x(0) = 0 = x(1)$ . So, in Eq. (5), we have the factor:

$$\begin{aligned}
I &= \frac{\imath}{2} \int_0^0 \mathcal{D}x \mathcal{D}p \exp \left\{ \frac{\imath}{2} \int_0^1 (p^2 - \dot{x}^2) d\tau \right\} \\
&= \sqrt{\frac{\imath}{4(2\pi)^3}}.
\end{aligned} \tag{7}$$

Given that

$$\int \mathcal{D}e \delta(\dot{e}) \mathcal{G}(e) = \mathcal{G}(e_0),$$

we arrive at the path integral representation for the propagator

$$\mathcal{F}(x_{out}, x_{in}) = \sqrt{\frac{\imath}{4(2\pi)^3}} \int_0^\infty \frac{de_0}{\sqrt{e_0^3}} \exp \left\{ -\frac{\imath}{2} \left[ e_0 \mathcal{M}^2 + \frac{\Delta x^2}{e_0} - \frac{s^2}{e_0} \right] \right\} \tag{8}$$

and  $s^2 > 0$  for the causal propagator. This expression was obtained along the same lines as those used elsewhere for the scalar particle[6]. On the other hand, in momentum space, the anyonic propagator has the form[7]

$$\tilde{\mathcal{F}}(p) = \frac{1}{(p_\mu - m S_\mu)^2 - m^2}. \tag{9}$$

Now, we consider the light-like case, for the anyon in a constant electromagnetic field  $A_\mu = -\frac{1}{2} F_{\mu\nu} x^\nu$ . Following[8], we perform the calculation in the representation over velocities, which is characterized by the absence of derivatives in time after integration over bosonic variables and arbitrary boundary conditions. The propagator, in a first step, can be written as

$$\begin{aligned}
\mathcal{F}(x_{out}, x_{in}) &= \sqrt{\frac{\imath}{4(2\pi)^3}} \int_0^\infty \frac{de_0}{\sqrt{e_0^3}} \exp \left[ -\frac{\imath}{2} \left( e_0 \mathcal{M}^2 + \frac{\Delta x^2}{e_0} - \frac{s^2}{e_0} \right) \right] \\
&\times \int \mathcal{D}v \delta^3 \left( \int v d\tau \right) \exp \left\{ \imath \int \left[ -\frac{v^2}{2} - g(\sqrt{e_0} v + \Delta x) A \right. \right. \\
&\quad \left. \left. \times \left( \sqrt{e_0} \int_0^\tau v(\tau') d\tau' + x_{in} + \tau \Delta x \right) \right] d\tau \right\},
\end{aligned} \tag{10}$$

where the new measure  $\mathcal{D}v$  has the form

$$\mathcal{D}v = Dv \left[ \int Dv \delta^3 \left( \int v d\tau \right) \exp \left\{ -\imath \int \frac{v^2}{2} d\tau \right\} \right]^{-1}. \tag{11}$$

For the particle in a constant electromagnetic field we can obtain for the propagator

$$\begin{aligned}
\mathcal{F}(x_{out}, x_{in}) &= \sqrt{\frac{i}{4(2\pi)^3}} \int_0^\infty \frac{de_0}{\sqrt{e_0^3}} \\
&\times \left[ \frac{\det L(g)}{\det L(0)} \right]^{-\frac{1}{2}} \left[ \frac{\det Q(g)}{\det Q(0)} \right]^{-\frac{1}{2}} \\
&\times \exp \left\{ \frac{i}{2} g x_{out} F x_{in} - \frac{i}{2} e_0 \mathcal{M}^2 - \frac{i}{2} \frac{s^2}{e_0} - \frac{i}{2e_0} \Delta x Q^{-1} \Delta x \right\}, \quad (12)
\end{aligned}$$

where

$$\begin{aligned}
L_{\mu\nu}(\tau, \tau') &= \eta_{\mu\nu} \delta(\tau - \tau') - \frac{1}{2} g e_0 F_{\mu\nu} \epsilon(\tau - \tau'), \\
Q &= \frac{2}{g e_0 F} \tanh \frac{g e_0 F}{2}.
\end{aligned}$$

Thus we have, finally, the expression for the propagator as

$$\begin{aligned}
\mathcal{F}(x_{out}, x_{in}) &= \sqrt{\frac{i}{4(2\pi)^3}} \int_0^\infty \frac{de_0}{\sqrt{e_0^3}} \left[ \det \frac{\sinh \frac{g e_0 F}{2}}{\frac{g e_0 F}{2}} \right]^{-\frac{1}{2}} \\
&\times \exp \left\{ \frac{i}{2} g x_{out} F x_{in} - \frac{i}{2} e_0 \mathcal{M}^2 - \frac{i}{2} \frac{s^2}{e_0} \right. \\
&\left. - \frac{i}{4} (x_{out} - x_{in}) g F \coth \frac{g e_0 F}{2} (x_{out} - x_{in}) \right\}. \quad (13)
\end{aligned}$$

If the electromagnetic field is turned off we obtain again the result Eq. (8) with  $s = 0$  and, for  $\alpha = 0$ , we obtain the path integral representation for the spinless particle propagator in (2+1)-dimensions.

In summary, we have obtained a path integral representation for the propagator of a free anyon Eq. (8) and its representation in momentum space Eq. (9) taking into account a continuous family of Lagrangians Eq. (4). These ones were obtained by a group-theoretical approach with minimal extension that preserves all canonical structure of the space-time and spin algebra. We also consider an anyon in a constant electromagnetic field. To obtain the propagator, a convenient gauge  $\dot{\sigma} = 0$ ,  $\dot{e} = 0$  was considered.

## REFERENCES

- [1] J. F. Schonfeld, Nucl. Phys. **B185** 157 (1981); R. Jackiw and V. P. Nair, Phys. Rev. **D43** 1933 (1991); C. Chou, V. P. Nair and P. Polychronakos, Phys. Lett. **B304** 105 (1993); S. Gosh, Phys. Lett **B338** 235 (1994); D. Dalmazi and A. de Souza Dutra, Phys. Lett. **B343** 225 (1995); J. L. Cortés and M. S. Plyushchay, Int. J. Mod. Phys. **A11** 3331 (1996) and references therein.

- [2] J. M. Leinaas and J. Myrheim, *Nuovo Cimento* **B37** 1 (1977); F. Wilczek, *Phys. Rev. Lett.* **48** 1144 (1982); **49** 957 (1991).
- [3] F. Wilczek, in *Fractional Statistics and Anyon Superconductivity* ( World Scientific, 1990).
- [4] D. Dalmazi and A. de Souza Dutra, *Phys. Lett.* **B414** 315 (1997) and references therein.
- [5] I. V. Gorbunov, S. M. Kuzenko and S. L. Lyakhovich, *Int. J. Mod. Phys.* **A12**, 4199 (1997) and references therein.
- [6] E. S. Fradkin and D. M. Gitman, *Phys. Rev* **D44** 3230 (1991).
- [7] W. da Cruz, *Mod. Phys. Lett.* **A14** 1933 (1999).
- [8] W. da Cruz and A. E. Gonçalves, preprint ( unpublished ); W. da Cruz, *J. Phys. A : Math. and Gen.* **30** 5225 (1997) and references therein.

DEPARTAMENTO DE FISICA, UNIVERSIDADE ESTADUAL DE LONDRINA, CAIXA  
POSTAL 6001, LONDRINA-PARANA, BRAZIL *E-mail address:* wdacruz@exatas.uel.br